SPECTRALARM AB105STR

Sounder unit A105N

Maximum output: 112 dB(A) @ 1 m

Nominal output: 106 dB(A) @ 1 m - tone 2

32 alarm tones

Xenon Strobe Flashing Beacon 5J @ 1 Hz

Three modes (DC Only): Flashing 1Hz (default) AB105STRDC24v/x

Flashing 1.5Hz (DC units Only) Double Strike (DC Units Only), Stage Switchable to Double

Strike (DC Units Only)

IP Rating: IP65

Temp: -25°C to +50°C

Unit weight: 1.15kg DC 1.30kg AC

Dimensions: 130mm(w) x 250mm(h)

1.5mm² terminals

For Lens colour options

x = in order code to be replaced with required

lens colour

R = RedA = Amber

B = Blue C = Clear

G = Green Y = Yellow

y = in order code to be replaced with required

housing colour

G = Grev R = Red Order code

Nominal voltage range

AB105STRDC12y/x 12VDC (10-15VDC) Beacon 600mA Sounder 50mA @ 12VDC

24VDC (18-30VDC)

Beacon 300mA Sounder 25mA @ 24VDC

AB105STRDC48v/x 48VDC (36-60VDC) Beacon 250mA Sounder 50mA @ 48VDC

AB105STRAC24v/x 24VAC (22-26VAC) Beacon 300mA Sounder 40mA @ 24VAC

AB105STRAC115y/x 115VAC (103-127VAC) Beacon 70mA Sounder 20mA @ 115VAC

AB105STRAC230v/x 230VAC (207-253VAC) Beacon 35mA Sounder 15mA @ 230VAC

Example: AB105STRDC24G/R

This example is for a

A105N sounder with strobe beacon

running on 24VDC

the housing is grey with a red lens.

ATTENTION: Installation must be carried out by an electrician in compliance with the latest codes and regulations.



ATTENTION: Disconnect from power source before installation or service to prevent electric shock.



ATTENTION: On strobe beacons allow a minimum of 2 minutes for hazardous high voltage to discharge from unit.



ATTENTION: Lens on unit will be hot allow to cool prior to removal.

2

AB105STR Sounder Tone **Settings Table**

For switch settings please note:-Where 1 is indicated the switch position is on. Where 0 is indicated the switch

Example:-

position is off.

Table shows 1 0 0 0 0 0 Switch setting On Off Off Off Off



| Stage 1 | Frequency Description | Switch 1 2 3 4 5 6 | Stage 2 | Stage 3 |
|---------|--|-----------------------|---------|---------|
| 1 | 340Hz Continuous | 000000 | Tone 2 | Tone 5 |
| 2 | 800/1000Hz @ 0.25 sec Alternating | 100000 | Tone 17 | Tone 5 |
| 3 | 500/1200Hz @ 0.3Hz sec Slow Whoop | 010000 | Tone 2 | Tone 5 |
| 4 | 800/1000Hz @ 1Hz SweepIng | 110000 | Tone 6 | Tone 5 |
| 5 | 2400Hz Continuous | 001000 | Tone 3 | Tone 20 |
| 6 | 2400/2900Hz @ 7Hz Sweeping | 101000 | Tone 7 | Tone 5 |
| 7 | 2400/2900Hz @ 1Hz SweepIng | 011000 | Tone 10 | Tone 5 |
| 8 | 500/1200/500Hz @ 0.3Hz SweepIng | 111000 | Tone 2 | Tone 5 |
| 9 | 1200/500Hz @ 1Hz - DIN PFEER P.T.A.P. | 000100 | Tone 15 | Tone 2 |
| 10 | 2400/2900Hz @ 2Hz Alternating | 100100 | Tone 7 | Tone 5 |
| 11 | 1000Hz @ 1Hz Intermittent | 010100 | Tone 2 | Tone 5 |
| 12 | 800/1000Hz @ 0.875Hz Alternating | 110100 | Tone 4 | Tone 5 |
| 13 | 2400Hz @ 1Hz Intermittent | 001100 | Tone 15 | Tone 5 |
| 14 | 800Hz 0.25 sec on, 1 sec off Intermittent | 101100 | Tone 4 | Tone 5 |
| 15 | 800Hz Continuous | 011100 | Tone 2 | Tone 5 |
| 16 | 660Hz 150mS on, 150mS off Intermittent | 111100 | Tone 18 | Tone 5 |
| 17 | 544Hz (100mS)/440 Hz (400m/S) - NF S 32-001 | 000010 | Tone 2 | Tone 27 |
| 18 | 660Hz 1.8 sec on, 1.8 sec off Intermittent | 100010 | Tone 2 | Tone 5 |
| 19 | 1.4KHz - 1.6KHz 1s, 1.6KHz - 1.4 KHz 0.5s - NFC48-265 | 010010 | Tone 2 | Tone 5 |
| 20 | 660Hz Contlnuous | 110010 | Tone 2 | Tone 5 |
| 21 | 554Hz/440Hz @ 1Hz Alternating | 001010 | Tone 2 | Tone 5 |
| 22 | 544Hz @ 0.875 sec Intermittent | 101010 | Tone 2 | Tone 5 |
| 23 | 800Hz @ 2Hz Intermittent | 011010 | Tone 6 | Tone 5 |
| 24 | 800/1000Hz @ 50Hz Sweeping | 111010 | Tone 29 | Tone 5 |
| 25 | 2400/2900Hz @ 50Hz Sweeping | 000110 | Tone 29 | Tone 5 |
| 26 | Bell | 100110 | Tone 2 | Tone 15 |
| 27 | 554Hz Contlinuous | 010110 | Tone 26 | Tone 5 |
| 28 | 440Hz Contlinuous | 1 1 0 1 1 0 | Tone 2 | Tone 5 |
| 29 | 800/1000Hz @ 7Hz Sweeping | 001110 | Tone 7 | Tone 5 |
| 30 | 300Hz Continuous | 101110 | Tone 2 | Tone 5 |
| 31 | 660/1200Hz @ 1Hz SweepIng | 0 1 1 1 1 0 | Tone 26 | Tone 5 |
| 32 | Two tone chime | 111110 | Tone 26 | Tone 15 |

DC UNIT MODE SELECTION









